

Product data sheet

Specifications



Starter, Definite Purpose, nonreversing, 20A, 3 pole, 3 phase, 120VAC coil, melting alloy overload, NEMA 1, +options

8911DPSG13V02

Product availability: Stock - Normally stocked in distribution facility

Main

Product	Definite Purpose Starter
Ampere Rating	20 A
Horsepower Rating	3 hp 230 V AC, 1 phase 7.5 hp 230 V AC, 3 phase 1.5 hp 115 V AC, 1 phase 7.5 hp 460 V AC, 3 phase 7.5 hp 575 V AC, 3 phase
Maximum Voltage Rating	600 V AC
Control Circuit Voltage	110 V AC 50 Hz 120 V AC 60 Hz
Phase	3 phase

Complementary

Enclosure Material	Painted sheet steel
Enclosure Rating	NEMA 1
Locked Rotor Amperes	120 A 230 V AC 100 A 460 V AC 80 A 575 V AC
Number of Poles	3P
Range	DPS
Overload Type	Melting alloy
Number of Thermal Units	3

Ordering and shipping details

Category	US10CP121381
Discount Schedule	0CP1
GTIN	785901081470
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	6.400 in (16.256 cm)
Package 1 Width	6.800 in (17.272 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 1 Length	10.600 in (26.924 cm)
Package weight(Lbs)	5.600 lb(US) (2.540 kg)

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
EU RoHS Directive	Compliant By Exemption

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Take-back	No