

3" x 2" Gangable Switch Boxes

1-1/2" & 2" Deep

Features


- Boxes – 1-1/2" & 2" deep
- Boxes – 7.5 - 10 cu in.
- Available with adjustable plaster ears, NM Clamps, MC Clamps where noted

Applications

- 3" x 2" Switch boxes can be installed in walls or ceilings for lighting fixtures, switches, receptacles or other outlet devices
- Switch boxes are used to bring power to a number of electrical devices where multiple conductor runs are split in two or more directions
- The adjustable plaster ears allow for an easy "cut in" when switches or outlets need to be added
- 2" boxes are gangable


Standard Material

- Galvanized steel




SBG410

NM Clamp
* Non-gangable




SBG420



SBG440

MC Clamp



SBG445

NM Clamp

Catalog Number	UPC	Description	Knockouts			Cubic Inches	Ship Case	Weight/Case
			Sides	Ends	Bottom			
SBG410	00002	1-1/2" deep with NM Clamp, non-gangable	---	4 pryouts	---	7.5	50	21
SBG420	00004	2" deep 1/2" KO	(4) - 1/2"	(2) - 1/2"	(2) - 1/2"	10	50	26
SBG440	00005	2" deep with MC Clamp	---	4 pryouts	(1) - 1/2"	10	50	27
SBG445	00003	2" deep with NM Clamp	---	4 pryouts	(1) - 1/2"	10	50	26