



FXCS Series Double 120V Pilot Light Cover With Device -Factory Sealed - Red Lens And Green Lens With Nameplates To Be Specified

By Killark
Catalog # [FXCS-0B30RL-GL](#)

FXCS Series - Aluminum Double 120V Pilot Light Cover With Device -Factory Sealed - Red Lens And Green Lens With Nameplates To Be Specified

Features

- Eliminates external sealing requirements.
- Lower installation cost.
- NEMA 3 weatherproof.
- Color coded wiring with more wiring space for easier field installation.
- Stainless steel captive screws for cover assembly.
- Lockout accessory available must be factory installed.
- Ground boss for grounding in the splice box.
- Device bodies and covers are copper-free cast aluminum alloy.
- Push button, selector switches and pilot light bodies are copper-free aluminum.
- Operating shaft in both push buttons and selector switches are stainless steel.

Application

SEAL-X Series is used to prevent the igniting of external hazardous atmospheres by the enclosed arcing devices in such areas as: hazardous locations due to the presence of flammable gases or vapors, combustible dusts or easily ignitable fibers or flyings

Specifications

CSA File Number	LR11714, LR11712
EU RoHS Indicator	Contact Manufacturer
Nema Rating	3
UL File Number	E53360, E12379
Hazardous Rating(s)	• Class I, Divisions 1 & 2, Groups C, D • Class I, Zones 1 & 2, Groups IIB, IIA • Class II, Divisions 1 & 2, Groups E, F, G • Class III, Divisions 1 & 2



Configuration

Back Box Type	FXB
---------------	-----

Current

Frequency Rating	50/60 Hz
Amperage Rating	0.25 A

Dimensions

Length	6.63 in
Weight	3.00 lb.
Height	4.38 in
Width	6 in
Gross Weight with Packaging	3
Dimensions	6.63 in x 6 in x 4.38 in

General

Color	Red-Green
Series	FXCS Series
UPC	783936201412
Type	Aluminum Factory Sealed Cover With Two Pilot Lights
Material	Copper-free aluminum

Logistics

Factory Sealed	Factory Sealed
Carton Quantity	5

Operational

Actuator	Double Pilot Light
----------	--------------------

Product Assets

- [Catalog \[English\]](#)
[Installation Manual \[English\]](#)
[Installation Manual \[French\]](#)