



XCS Series Control Station Cover - Spring Returned 2-Position Keyed Selector Switch Cover With Device - Return to Left - Keyed Different

By Killark
Catalog # [XCS-OK2L3F22D](#)

XCS Series - Aluminum Spring Returned 2-Position Keyed Selector Switch Cover With Device - Return to Left - Keyed Different

Features

- Copper free cast aluminum alloy.
- Ground flange joint between bolted cover and box provide required flame path.
- Push button, selector switches and pilot light operator bodies are copper-free aluminum.
- Operating shaft in both push buttons and selector switches are stainless steel.

Application

Hazardous locations due to the presence of flammable gases or vapors, combustible dusts, or easily ignitable fiber or flyings. Installations at petroleum refineries, chemical and petrochemical plants, and other processing or storage facilities where simil

Specifications

UL File Number	E53360
Buy America(n) Qualified	Contact Manufacturer
CSA File Number	LR11714
Hazardous Rating(s)	• Class I, Divisions 1 & 2, Groups C, D • Class I, Zones 1 & 2, Groups IIB, IIA • Class II, Divisions 1 & 2, Groups E, F, G • Class III, Divisions 1 & 2
EU RoHS Indicator	Contact Manufacturer
Conductor	
Number Of Poles	1
Configuration	
Back Box Type	SWB
Current	
Frequency Rating	50/60 Hz



Amperage Rating	10 A
Contact Rating	• 60A INRUSH @ 120 VAC • 30A INRUSH @ 240 VAC • 15A INRUSH @ 480 VAC • 12A INRUSH @ 600 VAC • 6A BREAKING @ 120 VAC • 3A BREAKING @ 240 VAC • 1.5A BREAKING @ 480 VAC • 1.2A BREAKING @ 600 VAC • 10A CARRYING @ 120 VAC • 10A CARRYING @ 240 VAC • 10A CARRYING @ 480 VAC

Dimensions

Height	4 in
Width	5.75 in
Length	7.563 in
Gross Weight with Packaging	1.6
Depth	2-3/4 in
Dimensions	7.563 in x 5.75 in x 4 in

General

Color	Black
UPC	783936891033
Type	Aluminum Cover With 2-Position Key Selector Switch
Material	Copper-free aluminum
Series	XCS Series

Operational

Actuator	2 Position Selector Switch
Action	Rotary

Product Assets

- [Catalog \[English\]](#)
- [Installation Manual \[French, English\]](#)
- [Installation Manual \[English\]](#)