

Product data sheet

Specifications

SQUARE D



NEMA Motor Starter, Type S, replacement coil, 208VAC 60Hz, 2 or 3 pole, NEMA size 3 starter and 8903SQ lighting

3107440044

Product availability: Stock - Normally stocked in distribution facility

Main

Product or Component Type	Coil
Accessory / separate part destination	Class 8502 type SE contactor Class 8903 type SQ lighting contactor Class 8910 type DPA12/SYD138 contactor

Complementary

NEMA size	3
[Ue] rated operational voltage	208 V AC 60 Hz
Inrush power in VA	700 VA
Average consumption	46 VA
Height	2.9 in (73 mm)
Width	2.6 in (65 mm)
Depth	0.082 in (2.093 mm)

Ordering and shipping details

Category	US1CP1018079
Discount Schedule	CP10
GTIN	785901226055
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.100 in (5.334 cm)
Package 1 Width	2.800 in (7.112 cm)
Package 1 Length	3.400 in (8.636 cm)
Package weight(Lbs)	12.800 oz (362.874 g)

Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Take-back	No