

Product data sheet

Specifications

SQUARE D



Transformer disconnect, 1000VA, 240x480VAC primary, 120VAC secondary, with outlet, Type 1

9070SK1000G1D1G13

Discontinued on: Jun 25, 2025

Discontinued

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product	Transformer Disconnect
Certifications	UL Listed CSA
Enclosure Type	NEMA 1 standard
Insulation Temperature	356 °F (180 °C)
Phase	1 phase
Primary Voltage	240 x 480 V
Power Rating	1000 VA
Secondary Voltage	120 V
Temperature Rise	115 °C
Electrical Connection	Screw clamp terminals
Type	SK

Ordering and shipping details

Category	US10CP821694
Discount Schedule	0CP8
GTIN	785901747109
Returnability	No
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	11.80 in (29.972 cm)
Package 1 Width	11.50 in (29.21 cm)
Package 1 Length	15.40 in (39.116 cm)
Package weight(Lbs)	38.001 lb(US) (17.237 kg)

Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained](#) >

[How we assess product sustainability](#) >

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
California proposition 65	WARNING: This product can expose you to chemicals including: Phenyl Glycidyl Ether, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
Take-back	No