

# Product data sheet

Specifications



## Meter accessory, EZ Meter-Pak, Q2M to QO circuit breaker adaptor

EZM125QOA

Product availability: Stock - Normally stocked in distribution facility

### Main

|                   |           |
|-------------------|-----------|
| Device short name | EZ        |
| Range of Product  | Meter-Pak |

### Complementary

|        |                   |
|--------|-------------------|
| Height | 3.6 in (91.4 mm)  |
| Width  | 4.5 in (114.3 mm) |
| Depth  | 5.4 in (137.2 mm) |

### Ordering and shipping details

|                   |              |
|-------------------|--------------|
| Category          | US10DE400027 |
| Discount Schedule | 0DE4         |
| GTIN              | 785901330486 |
| Returnability     | Yes          |
| Country of origin | MX           |

### Packing Units

|                              |                            |
|------------------------------|----------------------------|
| Unit Type of Package 1       | PCE                        |
| Nbr. of units in pkg.        | 1                          |
| Package 1 Height             | 3.600 in (9.144 cm)        |
| Package 1 Width              | 4.500 in (11.430 cm)       |
| Package 1 Length             | 5.400 in (13.716 cm)       |
| Package weight(Lbs)          | 9.600 oz (272.155 g)       |
| Unit Type of Package 2       | PAL                        |
| Number of Units in Package 2 | 252                        |
| Package 2 Height             | 40.000 in (101.600 cm)     |
| Package 2 Width              | 40.000 in (101.600 cm)     |
| Package 2 Length             | 48.000 in (121.920 cm)     |
| Package 2 Weight             | 169.000 lb(US) (76.657 kg) |

### Contractual warranty

|          |           |
|----------|-----------|
| Warranty | 18 months |
|----------|-----------|

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

| Environmental footprint                        |                                               |
|------------------------------------------------|-----------------------------------------------|
| Carbon footprint (kg CO2 eq, Total Life cycle) | 506                                           |
| Environmental Disclosure                       | <a href="#">Product Environmental Profile</a> |

Use Better

| Materials and Substances               |                                                                                                                                                                                                                                                                                             |
|----------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Packaging made with recycled cardboard | No                                                                                                                                                                                                                                                                                          |
| Packaging without single use plastic   | Yes                                                                                                                                                                                                                                                                                         |
| <a href="#">EU RoHS Directive</a>      | Compliant with Exemptions                                                                                                                                                                                                                                                                   |
| REACH Regulation                       | <a href="#">REACH Declaration</a>                                                                                                                                                                                                                                                           |
| California proposition 65              | WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a> |

Use Again

| Repack and remanufacture |                                          |
|--------------------------|------------------------------------------|
| Circularity Profile      | No need of specific recycling operations |
| Take-back                | No                                       |

Image of product / Alternate images

Alternative

---

MFG Model Number  
**EZM125QOA**



Use to install Square D  
125 amp breakers to  
Square D 225 amp base



Use with Square D Bolt-On  
QB, QD, QG or QJ 2-pole  
tenant breakers



Compatible with  
Square D EZM  
Branch devices only





MFG Model Number  
**EZM125QOA**



5.4 in

3.6 in

4.5 in

↑

**Dimensions**

### Compatible products

Metering Plug-On Adapter Kit  
MFG Model Number: EZM125QOA





Compatible for EZ Meter Pak products for Q2M to QO circuit breaker conversion

