

Product data sheet

Specifications

SQUARE D



Interior, I-Line, for OEM mounting, universal lugs/breaker, 400A, Al bus, 49.5in CB space, J-frame max.

HKA495S4

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Range	I-Line
Product or Component Type	Interiors

Complementary

Main Type	Universal Mains
Product Destination	Enclosure
Rated Current	400 A
Mounting Space	49.5 in (1257.3 mm)
Bus Material	Aluminium: busbar
Net Weight	100.002 lb(US) (45.36 kg)

Ordering and shipping details

Category	US1PE1A09481
Discount Schedule	PE1A
GTIN	3606486995952
Returnability	No
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	9.29 in (23.6 cm)
Package 1 Width	36.26 in (92.1 cm)
Package 1 Length	40.00 in (101.6 cm)
Package weight(Lbs)	174.98 lb(US) (79.37 kg)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint	
Environmental Disclosure	Product Environmental Profile

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No