

Product data sheet

Specifications



Panelboard accessory, NF, lug kit, feed thru, 125A, Al

NF125FTL

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product	Lug kit
Provided equipment	Screw set 1 Rail extension 2 Rail splice 2 Lug 4 Cover extension 1

Complementary

Material	Aluminium
Current Rating	125 A
Tightening torque	60.2...64.6 lbf.in (6.8...7.3 N.m) 0.02...0.3 in ² (13.3...177.3 mm ²) (AWG 6...350 kcmil)

Environment

Product Certifications	cULus
------------------------	-------

Ordering and shipping details

Category	US1PE1A08338
Discount Schedule	PE1A
GTIN	785901538684
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.00 in (5.08 cm)
Package 1 Width	14.25 in (36.195 cm)
Package 1 Length	20.50 in (52.07 cm)
Package weight(Lbs)	3.419 lb(US) (1.551 kg)

Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant
REACH Regulation	REACH Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

 Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No