


Product data sheet

Specifications



Panelboard accessory, NQ, deadfront kit, branch, 400A, 1 phase, 84 circuits

NQRPL84L4

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product	Cover plate
Accessory / separate part category	Replacement part

Complementary

Number of spaces	84
Device Application	panelboard interior
Current Rating	400 A
Tightening torque	275...300 lbf.in (31.07...33.9 N.m) (AWG 1/0...750 kcmil)

Ordering and shipping details

Category	US1PE1A00014
Discount Schedule	PE1A
GTIN	3606486139011
Returnability	No
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package weight(Lbs)	31.999 oz (907.185 g)

Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant
REACH Regulation	Free of Substances of Very High Concern above the threshold
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Take-back	No