

Product data sheet

Specifications



Busway Circuit Breaker Plug-in Unit 20A, QO, 4A Type 1 with 3 Receptacles

PBPQOR4A100M120

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product or Component Type	Plug-in unit
Range of Product	Powerbus
Number of Receptacles	3 duplex receptacles

Complementary

Line Rated Current	100 A
Busbar Configuration	4A L1 + L2 + N + L3
Number of Phases	3 phase
Circuit Breaker Type	QO, 20 A, 3 3 breakers
Number of openings	3 openings
Number of Receptacles	3 duplex receptacles

Ordering and shipping details

GTIN	3606487401421
Returnability	No

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	3.7 in (9.5 cm)
Package 1 Width	10.0 in (25.4 cm)
Package 1 Length	14.7 in (37.4 cm)
Package weight(Lbs)	13.007 lb(US) (5.9 kg)

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

 Environmental footprint	
Environmental Disclosure	Product Environmental Profile

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	Compliant By Exemption
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Bisphenol A (BPA), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Longer

 Lifetime extension	
Repair	No

Use Again

 Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No