

Product data sheet

Specifications



Circuit breaker accessory, I-Line, sub feed lugs, 1200A, 350kcmil to 600kcmil

SL1200P6

Product availability: Stock - Normally stocked in distribution facility

Main

Range of Product	I-Line
Product or Component Type	Sub-feed lug
Device Application	Panelboard

Complementary

Line Rated Current	1200 A
Material	Aluminium
Mounting Mode	By screws
AWG gauge	3 x 350...600 kcmil aluminium/copper
Mounting Location	Inside the enclosure
Protection Type	Circuit breaker protection
Type of Installation	Indoor installation
Height	9.02 in (229 mm)

Environment

Product Certifications	UL
------------------------	----

Ordering and shipping details

Category	US10DE201250
Discount Schedule	0DE2
GTIN	785901851875
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	10.800 in (27.432 cm)
Package 1 Width	18.000 in (45.720 cm)
Package 1 Length	12.300 in (31.242 cm)
Package weight(Lbs)	13.221 lb(US) (5.997 kg)

Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
California proposition 65	WARNING: This product can expose you to chemicals including: DINP, which is known to the State of California to cause cancer, and DIDP, which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
Take-back	No